Installation Sheet) KSR6540-6541

Escala Pro

Linear Track Fitting

Available Finish: White

retain them for future reference. Read these instructions before commencing installation &



Important Information

ensuring the installation complies to current IEE wiring regulations & local building KSR will not accept responsibility for any claims arising from a sub-standard installation. system only. Any damaged parts should be replaced as soon as possible. control. These products are designed for use with the Escala Pro single circuit track It is recommended that the track system is installed and fitted by a qualified electrician

lmportant User Advice


Always switch off mains supply before installing or servicing This product is designed to be used indoors only.

Installation Procedure


Familiarize yourself with the way the luminaire attaches to the track and ensuring the correct polarity KSR open the lever(s) and insert the luminaire into track with the locking lever opposite the Live side (shown by the line on the track) then turn the lever anti-clockwise until the locking lever locks into the track lever touching the track, never force the lever see Fig.1.

KSR6541 **KSR6540** 1140mm 570mm 37mm 28mm

Fig. 1



track with the lever(s) opposite the live line on the track



1, Open lever(s) and insert in to

in to track



to lock/energise track 3. Turn lever(s) Anti-Clockwise



Product Code

Wattage

CCT

Lamp Details

KSR6541 KSR6540

36W 18W

4000K 4000K

1554 3000

>94 >94 CRI Ra:

Lumens

Finished



E-mail: aftersales@ksrlighting.com KSR Lighting Aftersales: 023 92 674343